

GV-Keyboard V3 for GV-System / GV-VMS



The GV-Keyboard V3 is designed to program and operate GV-System / GV-VMS, and it can also be connected with PTZ cameras directly for PTZ control.

Key Features

- Up to 36 GV-Systems / GV-VMS supported
- Up to 8 monitors for Digital Matrix, TV Quad and Spot Monitor applications workable with multiple Keyboards
- PTZ camera control
- OSD panel supported

Specifications

		GV-System (GV-DVR/ NVR)	GV-VMS
OS Supported	32-bit	Windows XP / Vista / 7 / 8 / Server 2008	N/A
	64-bit	Windows 7 / 8 / Server 2008 R2 / Server 2012	Windows 7 / 8 / 8.1 / 10 / Server 2008 R2 / Server 2012 R2
System Supported		GV-System V8.4 or later	GV-VMS V14.10 or later
Output	USB	USB 2.0	
	DVR/RS-485+ DVR/RS-485-	Connects to GV-NET card, GV-NET/IO card, GV-Hub V2 or GV-COM V2	
	PTZ/RS-485+ PTZ/RS-485-	Connects to PTZ cameras	
	PTZ/RS-422+ PTZ/RS-422-		
Communication	RS-485	9,600 bps (between the keyboard and GV-System)	
	RS-485 / 422	2,400 ~ 115,200 bps (between the keyboard and PTZ cameras)	
Power	DC In	DC 12V 1A	
Environmental Conditions	Operating Temperature	0~50°C / 32 ~122°F	
	Humidity	5%~95% (non-condensing)	
Dimensions (L x W x H)		161 x 300 x 45 mm / 6.34 x 11.81 x 1.77 in	
Quick Strat Guide		GV-Keyboard V3	

Note:

1. Currently, GV-Keyboard V3 does not support embedded operating systems.
2. All specifications are subject to change without notice.