

## GV-Relay V2



CE FC

GV-Relay V2 is designed especially for driving higher voltage output devices, and works in conjunction with other GeoVision devices, such as GV-Video Server, GV-Compact DVR, GV-IP Camera, GV-DSP LPR, GV-I/O USB Box and GV-NET/IO Card V3.1.

GV-Relay V2 provides 4 relay outputs, and each output can be set as normally open (NO) or normally closed (NC) independently as per your requirement.

Specifications	
Relay Output	RL1~RL4
Relay Control Source	+5V, COM, DO1 - DO4 Connecting Outputs of GV-Video Server / GV-Compact DVR / GV-IP Camera / GV-DSP LPR / GV-I/O USB Box / GV-NET/IO Card V3.1
Relay Status	NO (Normally Open) and NC (Normally Closed) for each output
Relay Capacitance	10A 250V AC / 10A 125V AC / 5A 100V DC
Relay On Time	8ms
Relay Off Time	5ms
Dimensions (W x H x D)	120 x 26 x 93 mm / 4.72 x 1.02 x 3.66 in
Installation Guide	<a href="#">GV-Relay V2</a>

**Note:** All specifications are subject to change without notice.